

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 969 656 A1

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
05.01.2000 Bulletin 2000/01

(51) Int. Cl.⁷: H04N 1/41, H04N 7/28

(21) Application number: 99304633.3

(22) Date of filing: 15.06.1999

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(30) Priority: 29.06.1998 US 106732

(71) Applicant: XEROX CORPORATION
Rochester, New York 14644 (US)

(72) Inventors:
• Nguyen, Uoc H.
Long Beach, California 90807 (US)

• Claproth, Abraham E.
Culver City, California 90230 (US)
• Nguyen, Kien T.
Torrance, California 90501 (US)
• Lin, Weili
Irvine, California 92612 (US)

(74) Representative:
Skone James, Robert Edmund
GILL JENNINGS & EVERY
Broadgate House
7 Eldon Street
London EC2M 7LH (GB)

(54) Compression for image boundaries

(57) In a system where two types of data are to be compressed using hierarchical vector quantization (HVQ), it would be typical for there to be two compression tables, one optimized for each type of data. A

boundary between the two types may occur within a block to be compressed. In this case, a third table, optimized for a block having both types of data, is used.




FIG. 8

Description

[0001] When data must be transmitted or stored it is usually compressed first, to reduce the transmission time or storage requirement. This is especially true of image data which can consist of four color separations of 8-bit pixels.

[0002] One method of compression is "hierarchical vector quantization" (HVQ), where a block of data can be reduced to a single codeword in a number of steps. This method is described in U.S. Patent Number 5,602,589, and is incorporated by reference herein. This procedure can be explained most clearly by the use of a numerical example in connection with Fig 1a of that patent. Assume that a 2 by 4 pixel block, 8 bits per pixel, is to be compressed to one 9-bit number. First, each pair of pixels is applied to a stage 1 look up table (LUT) containing 9-bit code words, each code word being associated with a two-pixel bit pattern. The table is set up so that if an exact match of the input pixel bits is not available, then a codeword associated with the closest match is output instead. The ultimate output of this stage 1 is four codewords, each describing the closest match to the bit pattern of the two input pixels. Since the exact match frequently is not possible, this compression is inherently lossy to some extent. The output of the first stage is four 9-bit codewords.

[0003] Assuming this amount of compression is not sufficient, these four codewords, each representing the bit pattern of a 1 by 2 pixel block are next applied to two stage 2 tables, resulting in a total of two 9-bit output codewords, each representing the bit pattern of a 2 by 2 pixel block. If the compression is still insufficient, these two are applied to the stage 3 table to yield the final output word, which is associated with a 2 by 4 pixel block. It can now be seen that this method is hierarchical in that a plurality of stages are used, it involves vectors since the input pixels have a directional relationship with each other, and is quantized in that a number of levels can be implemented to achieve any degree of compression.

[0004] For decompression, each codeword is simply applied to a 256 K by 64 bit LUT which outputs the bit pattern of the entire 8-pixel block.

[0005] In accordance with the present invention, a method for compressing blocks of pixels, each block containing a printing hint that identifies the type of block comprises using the hint to select one of at least three encoding means for encoding the block, and using the selected encoding means to encode the block.

[0006] In a printing system which uses HVQ, the data is supplied to the lossy compressor in blocks of pixels, each block being text, contone, halftone, etc. So that the compressor may configure itself optimally for the kind of data being received, the front end may supply to the compressor a mask which determines the boundaries between different kinds of data, and printing hints which

specify which configuration should be used for the data that falls within each mask. In this system the mask edges must be aligned with the block edges.

[0007] The system can be improved by a system for determining if there is a boundary within a block, which can be referred to as a transition block. For example, if a boundary between a text character and a contone picture runs through a block, then a printing hint will be sent to the compressor, and table values optimized for transition blocks can be selected for that block. This would improve system performance by allowing the compressor to operate with less loss.

[0008] In one implementation, the process determines whether a block of pixels to be compressed is either of two types of image data, or contains a boundary between the types, so that the lossy compressor used to compress the block will be optimized for the first or second type of data, or for a transition between the two.

[0009] Some examples of methods according to the present invention will now be described with reference to the accompanying drawings, in which:-

Figure 1 is an HVQ encoder which has a parallel error channel;

Figure 2 is the decoder for the arrangement of Figure 1;

Figure 3 is a one-channel arrangement for coding a pixel split into its most and least significant bits;

Figure 4 is a one-channel arrangement for decoding a pixel split into its most and least significant bits;

Figure 5 is a two-channel arrangement for coding a pixel split into its most and least significant bits;

Figure 6 is a decoder for the coder of Figure 5;

Figure 7 shows three prices of rotating or mirror imaging an image using HVQ compression;

Figure 8 shows a boundary between blocks of different sizes; and,

Figure 9 shows a boundary between blocks of the same size.

[0010] The basic HVQ system can be improved by adding an error channel as shown in Figure 1. In the upper channel the grayscale byte map 16 is applied in the usual way to an HVQ encoder 10, the output is losslessly compressed in an LZ encoder 11, and the result is sent to the decoder, usually in the form of 8 to 10-bit words.

[0011] In addition, the output of the HVQ encoder is sent to a decoder 12 in scanline format which produces a version of the original byte map which may be different from the original because of errors possibly introduced by the lossy encoder. The two byte maps are then subtracted 13, pixel by pixel, to produce error terms which, if added to the output codeword, will produce the original byte map. This subtraction can also be done by using an exclusive OR, which is simpler and faster and does not require a sign bit. These error terms, each a

signed quantity 8-bits wide or less, can then be compressed in an LZ encoder 15 and sent to the decoder in parallel with the original output. The larger the error term, the less will be the compression ratio. In practice, small errors are not visually detectable. To limit the degradation of the compression ratio, the error term can be limited to a few most significant bits, three for example, in quantizer 14. Normally, the amount of error for a pixel will not be large enough to show up in the few MSB's, in which case there will be no error term at all.

[0012] The quantized error decoder is shown in Figure 2. The compressed code words are LZ decoded in decoder 21 and HVQ decoded in decoder 22 to produce one term for the adder 23. The compressed quantized errors are LZ decoded in decoder 24 and applied as the other term to the adder 23, the output of which is output video. The adder 23 can either be an adder adding a sign bit and seven bits, or an exclusive OR if one was used to generate the error term in the encoder.

[0013] Figure 3 shows the arrangement when a single code word 31 is split into most and least significant parts, 32, 33, and where only the least significant bits are compressed. In this case bits 0 through 4 are sent through lossy compressor 35 while bits 5 through 7 are not. Both are then compressed using lossless LZ compression and output to the decoder shown in Figure 4. Here again, both channels are LZ decompressed 41,42 while only the LSB's are HVQ decoded 43. The two resultant parts are then exclusive ORed 44 together to be applied to the decoding look up table.

[0014] Figure 5 is a system where a single pixel is separated into a least significant segment and a most significant segment, and where a separate and different compression process 54-57 is used for each segment, the least significant bits being more compressed. The original pixel is separated into its most significant bits 52 and least significant bits 53. The result is that the most significant bits, being the most important, are less compressed while compression for the least significant bits has a better compression ratio. A programmable look-up table could be used to split the input pixel into any two segments other than the 3 - 5 split shown.

[0015] Figure 6 is the decoder for the encoder of Figure 5. The two compressed outputs of Figure 5 are applied to LZ decoders 61, 62 and HVQ 63, 64 decoded. Then both are applied to an exclusive OR gate 65 to assemble the entire pixel. Of course, if the encoder used some other combination of encoders, the decoder would use the same form of decoding. That is, more generally, the data words in a string can be divided into more and less significant bits to create two parallel strings, and then compressed using any two methods of compression where the greater compression is applied to less significant bits.

[0016] HVQ compression is easily adapted to image rotation and mirror imaging as shown in Figure 7. The process is shown here using the example of an original image that is four pixels high and sixteen pixels wide,

and must be rotated ninety degrees clockwise and mirror imaged.

[0017] Step 1 is the usual compression process of reducing the eight 8-pixel segments to eight codewords Cw1 to Cw8. Step 2 is the step of rearranging the codewords into the rotated and mirror imaged order. This hardware can be in the form of wiring where the second word in, for example Cw2, is connected to the third word out, as shown. Step 2 can have several sets of wiring, each set delivering a different rotation. Finally, decoding step 3 uses a look-up table to produce a pixel pattern for each segment that is properly oriented. Here again, several tables can be used to produce various orientations.

[0018] Printing hints may be incorporated into the original data supplied by the user in the original page description language to indicate to the printer how the data may best be printed. For example, a hint word may be two bits in length, and indicate one of four possibilities, that the following data is text, contone, graphics, etc. For example, if the printer is receiving data that originated as a computer generated graphic it may use a different halftone screen than it would if the original data was screened in from a photograph.

[0019] Printing hints may be added to any HVQ channel as shown in Figure 5. Assume that for each 4 pixel block entering into the HVQ encoder 54 there is produced one codeword 9 bits in length, contained in two 8-bit bytes, so that the first 8 bits are contained in the first byte and the last bit is contained in the second byte. Then the 2-bit hint is added. Now, each codeword plus hint is 11 bits, still contained in two bytes. The LZ encoder looks at a string of bytes, perhaps 256 bytes in length, and determines the location and size of the most recent identical pattern match. To the extent that the hint changes once or twice within that string, there will be a slightly decreased amount of compression in comparison to the amount that would have resulted with no hints. However, to the extent that the hint does not change during that time, there is no decrease in compression at all. The result is that printing hints can be supplied after an HVQ compressor but before the lossless compressor with very little effect on the compression ratio. At the output side, after the code words are LZ decompressed, but before being decoded, the hints can be extracted for later use.

[0020] The losses of an HVQ compressor can be further minimized by choosing codewords and output data patterns that have the best chance of matching the actual input data patterns. For example, first consider text. If text pixels are being encoded in 4 by 2 pixel groups, and the four input pixels in one line are black, dark gray, light gray and white, and the input video was scanned-in text, the data most likely originally was a boundary between a black letter and a white space, so the output pixel pattern could be black, black, white, white. On the other hand, if the original input data was a scanned-in computer generated graphic, the four pixels

are more likely to be a smooth decrease in density from black to white. The actual determination of the encoder codewords and patterns in the decoder look-up table are determined by statistical analysis. A representative group of text and graphic documents are passed through a test program and the best values are generated for each type.

[0021] A complication arises when a boundary passes through an input block of pixels, in which case neither text nor graphic values can be used for the entire block. The solution is to supply a third set of codewords and patterns which are generated specifically for this boundary condition. In this case a set of documents containing both text and graphics would be analyzed to produce one set of patterns, which would be used when a boundary, mixed, condition is determined to be within the block.

[0022] The boundary condition is sensed by observing the printing hints. For example, a rectangular scanned-in picture is typically located on a page of text by its x,y coordinates. When the raster output scanner beam is within the coordinates, the printing hints will indicate to the printer which codewords, look-up table entries and halftone screens to use. If the hint changes from picture to text within the block, for example, then the encoder knows that a boundary exists within the block.

[0023] In all cases the block size must be maintained. Figure 8 is an example of a transition between text and contone. Since different block sizes can be used in HVQ encoders for different kinds of data, the block size for the text is shown here as 2 by 2 pixels to allow greater edge detail while the block size for contone is shown as being 4 by 2 to allow for greater compression.

[0024] If a boundary is within a 2 by 2 pixel block, that block is encoded and decoded using boundary values. In addition, any contone pixels to the right of the boundary such as pixel 81 are also treated as a boundary pixels if necessary so that all remaining pixels to the right of the boundary line will be within 4 by 2 pixel blocks. Similarly, in Figure 9, showing a boundary between 4 by 2 pixel blocks of text and contone, 2 by 2 pixel boundary blocks are used in pairs so that all remaining blocks will be 4 by 2.

Claims

1. A method for compressing blocks of pixels, each block containing a printing hint that identifies the type of block the method comprising the steps of:
 - using the hint to select one of at least three encoding means for encoding the block, and
 - using the selected encoding means to encode the block.
2. A method according to claim 1, wherein each hint indicates that the data represents one of text, contone and graphics.
3. A method according to claim 1 or claim 2, wherein the hint identifies the block as one or another type of data, or as a boundary block containing both types of data.
4. A method according to any of the preceding claims, wherein the encoding means comprise compressors, one optimized for a block containing a boundary.
5. A method according to any of the preceding claims, wherein the encoding means use hierarchical vector quantization.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 99 30 4633

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (InCl.7)
X	EP 0 358 815 A (OCÉ-NEDERLAND B.V.) 21 March 1990 (1990-03-21) * the whole document *	1-4	H04N1/41 H04N7/28
X	US 5 517 327 A (MUNEHIO NAKATANI ET AL.) 14 May 1996 (1996-05-14) * abstract * * column 5, line 44 - line 61 *	1	
P.X	EP 0 856 988 A (HEWLETT-PACKARD COMPANY) 5 August 1998 (1998-08-05) * the whole document *	1-4	
A	US 3 215 773 A (J. B. CHATTEN ET AL.) 2 November 1965 (1965-11-02)		
A	US 4 553 172 A (YAMADA MITSUHIKO ET AL.) 12 November 1985 (1985-11-12)		
A	WO 91 01609 A (GRAPHIC EDGE) 7 February 1991 (1991-02-07)		
			TECHNICAL FIELDS SEARCHED (InCl.7)
			H04N
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 16 November 1999	Examiner De Roeck, A
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

EPO FORM 1503 03 92 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 30 4633

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

16-11-1999

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 358815 A	21-03-1990	DE 3881392 T	21-10-1993
		JP 2105978 A	18-04-1990
		JP 2818448 B	30-10-1998
		US 5073953 A	17-12-1991
US 5517327 A	14-05-1996	JP 7058961 A	03-03-1995
		JP 7038761 A	07-02-1995
		JP 7050754 A	21-02-1995
		US 5875041 A	23-02-1999
		US 5841551 A	24-11-1998
EP 856988 A	05-08-1998	JP 10269350 A	09-10-1998
US 3215773 A	02-11-1965	NONE	
US 4553172 A	12-11-1985	JP 1023032 B	28-04-1989
		JP 1538859 C	16-01-1990
		JP 58157255 A	19-09-1983
		DE 3308468 A	22-09-1983
		FR 2523389 A	16-09-1983
		GB 2117208 A,B	05-10-1983
WO 9101609 A	07-02-1991	DE 69026505 D	15-05-1996
		EP 0483279 A	06-05-1992
		US 5226175 A	06-07-1993

THIS PAGE BLANK (USPTO)